



### Power derating



### Pinch-off current Temperature



### CRD in parallel

The use of CRD in parallel increases their current handling capabilities.

### Increasing the voltage range using a zener diode

Connecting zener diodes in series with the line ensures that the current is constant in high-voltage area.



### The compensation of current reduction due to self heating

Placing resistors in parallel with CRD can correct any current decrease when the applied voltage increases. The following values are typical for correction resistors.

E-102	1MΩ	E-352	82kΩ
E-152	390kΩ	E-452	56kΩ
E-202	240kΩ	E-562	39kΩ
E-272	120kΩ		



Compensative resistor is not necessary if the current value is less than 1 mA.



### Dynamic characteristics (saturation characteristics)



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Semitec:

[E-101](#) [E-102](#) [E-103](#) [E-123](#) [E-152](#) [E-153](#) [E-183](#) [E-202](#) [E-272](#) [E-301](#) [E-352](#) [E-452](#) [E-501](#) [E-562](#) [E-701](#) [E-822](#)  
[S-101T](#) [S-102T](#) [S-103T](#) [S-123T](#) [S-152T](#) [S-153T](#) [S-183T](#) [S-202T](#) [S-272T](#) [S-301T](#) [S-352T](#) [S-452T](#) [S-501T](#) [S-562T](#) [S-701T](#) [S-822T](#)